

**FRS / GMRS Comparative Frequency Assignments, F.C.C. Part 95 “Citizens Radio Service”**

<b>Radio Channel</b>	<b>Frequency Repeater Output</b>	<b>Frequency Repeater Input</b>	<b>FRS Channel</b>	<b>FRS Output</b>	<b>GMRS Channel</b>	<b>Motorola Channel</b>	<b>GMRS Output</b>	<b>Notes</b>
01	462.5625	--	1	500 mW	9	1	5 W	Unofficial national calling channel
02	462.5875	--	2	500 mW	10	2	5 W	
03	462.6125	--	3	500 mW	11	3	5 W	
04	462.6375	--	4	500 mW	12	4	5 W	
05	462.6625	--	5	500 mW	13	5	5 W	
06	462.6875	--	6	500 mW	14	6	5 W	
07	462.7125	--	7	500 mW	15	7	5 W	
08	467.5625	--	8	500 mW	--	--	--	
09	467.5875	--	9	500 mW	--	--	--	
10	467.6125	--	10	500 mW	--	--	--	
11	467.6375	--	11	500 mW	--	--	--	
12	467.6625	--	12	500 mW	--	--	--	
13	467.6875	--	13	500 mW	--	--	--	
14	467.7125	--	14	500 mW	--	--	--	
15	462.5500	467.5500	--	--	1	15	50 W	
16	462.5750	467.5750	--	--	2	16	50 W	
17	462.6000	467.6000	--	--	3	17	50 W	
18	462.6250	467.6250	--	--	4	18	50 W	
19	462.6500	467.6500	--	--	5	19	50 W	Do not use near Canadian border
20	462.6750	467.6750	--	--	6	20	50 W	Unofficial emergency/traveler assistance channel (Use PL 141.3)
21	462.7000	467.7000	--	--	7	21	50 W	Do not use near Canadian border
22	462.7250	467.7250	--	--	8	22	50 W	

**Note:** Red text indicates F.C.C. licensed operation only.

**Note on GMRS repeater assignments:** Eight (8) additional frequencies are available to GMRS for use only as repeater inputs. Commercial equipment and owner permission is required to access them.

**Note on Motorola channel numbering:** Be aware Motorola assigns GMRS channel numbers to coincide with FRS assignments. This is at odds with the standard F.C.C. channel numbering scheme.

**Note on Midland’s “Extra Channels”:** These are standard FRS/GMRS channels with precoded PL tones